

May 9, 2003

Log #: TSB-0327

9p23 Portable Telephone Administration Menu

Overview


This Technical Service Bulletin will address the Administration Menu access (also known as “Limited” or “Full” menu) which can now be set in the 9p23 Portable Telephone with software release R2A or higher.

The Administration menu access has been introduced in order for a system administrator to limit an end-user’s ability to change certain handset characteristics as follows:

- Eliminates everything in <options> selection under the “Messaging” menu except 1) Delete All Read and 2) Invert Text.
- Eliminates the “Settings” menu entirely.
- Eliminates the “Sounds” menu entirely (**Note:** Caregivers will still be able to invoke the “ringer mute” function by entering “Menu, #” to mute the ringer at night).

Access to Administration Menu

Limited or Full menu access is set by entering the Administration Menu under Settings. This menu is only available by entering the number **266344** (CONFIG) and Menu Down.
Note: The portable telephone must be powered up and in idle state.



Administrator Configurable Limit Menu Setting

Menu → 4) Settings → 3) Administration → 1) Limit Menu




Selecting *On* will limit the end user(s) to Messages and Phone Book menus only and selecting *Off* will allow the end user(s) to a Full menu option. The menu default is Off.

May 9, 2003


Log #: TSB-0327

Administrator Configurable Set Defaults

Menu → 4) Settings → 3) Administration → 2) Reset Defaults



This allows administrators to reset the phones default factory setting from the administration menu. Press **Ok**.




Administrator Configurable SMS Delay Setting


Menu → 4) Settings → 3) Administration → 3) SMS Delay



Menu → 4) Settings → 3) Administration → 3) SMS Delay → 1) 1 Second



Menu → 4) Settings → 3) Administration → 3) SMS Delay → 2) 3 Seconds



Menu → 4) Settings → 3) Administration → 3) SMS Delay → 3) Wait for dial tone



The SMS Delay setting is configurable to be 1 Second, 3 Seconds or wait for dial tone. With 9p23 software release R2B or higher, the default SMS delay is *wait for dial tone*. Select either one of the 3 selections and press **Confirm**.

May 9, 2003


Log #: TSB-0327

Current 9p23 SMS Default Settings and its Associated Release:


- R1A. No configurable SMS delay (fixed at 3 seconds for each “-“)
- R1C. No configurable SMS delay (fixed at 3 seconds for each “-“)
- R2A. 1 Second delay for each “-“
- R2B or higher. Wait for dial tone

Administrator Configurable Headset Type Setting

Menu → 4) Settings → 3) Administration → 4) Headset Type



Menu → 4) Settings → 3) Administration → 4) Headset Type → 1) Normal



Menu → 4) Settings → 3) Administration → 4) Headset Type → 2) Industrial



This setting allows the system administrator of a site to select between pre-set gain levels designed for the specific audio requirements of either a normal style (low noise environment) headset or an industrial style headset (specifically designed headset for use in louder environment). Press **Select**. Choosing between the two headset types requires that the phone be rebooted between any selections before any changes take effect.